


L- and C series Amplifiers Firmware 2.0.5 Release Notes

Firmware 2.x is required for L- and C series amplifiers to work with SONICUE 1.1 and higher
2.0.5 adds the option to reset locked amplifiers to factory default.

Press and hold the encoder button for 5+ seconds during start up (LCD display shows the Dynacord logo), this will get you to a dialog: "Reset to factory default: YES/NO".

L- and C Series Amplifiers Firmware 2.0.4 Release Notes

2.0.4. fixes a bug with control port (OUT) behavior on C Series.



Status / Behavior	FAULT	READY
	contacts 1-3 shorted	contacts 2-3 shorted
No mains present	x	
Switch in "STANDBY"		X (fixed bug)
During start up	x	
Switch in "POWER"		x
Amp in protect (Fault)	x	

Note: 2.0.X does not support SONICUE 1.0 and MARC software.

L/C Amplifier Firmware Update

Updating L/C Series amplifiers is accomplished via SONICUE. Follow the instructions below:

1. Open SONICUE
2. In Setup/Design choose Network Scan and drag in the Amplifier which should be updated
3. Navigate to Setup/Firmware and select the amplifier you dragged in

4. The opened flyout enables you to select the firmware which should be loaded onto the amplifier
5. Wait for the update to be finished